




Referenz-Verlegearten			Anzahl Stromkreise	Nennauslösestromstärke (A) des der Leitung vorgeschalteten Überstromunterbrechers (z.B. LS)													
				10	13	16	20	25	32	40	50	63	80	100	125	160	
A		Verlegeart A: Aderleitung in Rohr in wärmege­dämmt­er Wand	1	1.5	1.5	2.5	4	4	6	10	16	25	35	50	70	95	
A2		Verlegeart A2: Kabel in Rohr in wärmege­dämmt­er Wand	1	1.5	1.5	2.5	4	6	10	10	16	25	35	50	70	120	
B			1	1.5	1.5	1.5	2.5	4	6	10	10	16	25	35	50	70	
B2				1	1.5	1.5	1.5	2.5	4	6	10	16	16	25	35	50	95
				2	1.5	1.5	2.5	4	4	6	10	16	25	35	50	70	95
				3 - 4	1.5	1.5	2.5	4	6	10	10	16	25	35	50	70	120
				5 - 8	1.5	2.5	2.5	4	6	10	16	16	25	35	70	95	120
				9 - 15	1.5	2.5	4	4	6	10	16	25	35	50	70	95	
Verlegeart B2: Kabel in Rohr auf Holz­wand, Kabel in Installationskanal, Kabel in Rohr in Beton oder Mauerwerk																	